




SASK 51.6



Jisticí transformátor proudu násuvný



Primární pas 50 x 12 mm
40 x 30 mm
Primární vodič x 40 mm
Šířka 95 mm
Výška 116 mm



Primární jmenovitý proud [A]	Jmenovitá zátěž [VA]	Sekundární proud [A] / Třída přesnosti			
		5 A tř. 5P5 Obj. číslo	5 A tř. 10P5 Obj. číslo	5 A tř. 5P10 Obj. číslo	5 A tř. 10P10 Obj. číslo
150	1,5	S37-1606C	S37-1607C		S37-1609C
	2,5	S37-1606D	S37-1607D		S37-1609D
	5	S37-1606F	S37-1607F		
200	1,5	S37-1706C	S37-1707C	S37-1708C	S37-1709C
	2,5	S37-1706D	S37-1707D	S37-1708D	S37-1709D
	5	S37-1706F	S37-1707F		
250	2,5	S37-1806D	S37-1807D	S37-1808D	S37-1809D
	5	S37-1806F	S37-1807F		
300	2,5	S37-1906D	S37-1907D	S37-1908D	S37-1909D
	5	S37-1906F	S37-1907F		
	7,5		S37-1907G		
400	10		S37-1907H		
	2,5	S37-2006D	S37-2007D	S37-2008D	S37-2009D
	5	S37-2006F	S37-2007F	S37-2008F	S37-2009F
	7,5	S37-2006G	S37-2007G		
500	10	S37-2006H	S37-2007H		
	15		S37-2007J		
	2,5	S37-2106D	S37-2107D	S37-2108D	S37-2109D
	5	S37-2106F	S37-2107F	S37-2108F	S37-2109F
600	7,5	S37-2106G	S37-2107G		
	10	S37-2106H	S37-2107H		
	15	S37-2106J	S37-2107J		
	2,5	S37-2206D	S37-2207D	S37-2208D	S37-2209D
750	5	S37-2206F	S37-2207F	S37-2208F	S37-2209F
	7,5	S37-2206G	S37-2207G		
	10	S37-2206H	S37-2207H		
	15	S37-2206J	S37-2207J		
1000	2,5	S37-2306D	S37-2307D	S37-2308D	S37-2309D
	5	S37-2306F	S37-2307F	S37-2308F	S37-2309F
	7,5	S37-2306G	S37-2307G		
	10	S37-2306H	S37-2307H		
1500	15	S37-2306J	S37-2307J		
	2,5	S37-2506D	S37-2507D	S37-2508D	S37-2509D
	5	S37-2506F	S37-2507F	S37-2508F	S37-2509F
	7,5	S37-2506G	S37-2507G	S37-2508G	S37-2509G
2000	10	S37-2506H	S37-2507H		
	15	S37-2506J	S37-2507J		

		Obj. číslo
	Přichytka na DIN lištu	
	Plombovací krytka E	59044